

IMAGE FORMING APPARATUS

AND

METHOD OF CONTROLLING IMAGE FORMING APPARATUS

5 BACKGROUND OF THE INVENTION

Field of the Invention

The present invention relates to control of an electrophotographic printer having a non-volatile memory inside the printer or in a functional portion capable of transmitting and receiving data to and from the main body of the printer and detachably attachable to the main body.

Related Art

Fig. 9 is a block diagram showing a configuration of a conventional printer control portion.

Numeral 101 designates a printer controller, which executes communication with a host computer, which receives image data to expand the received image data into information for the printer to be able to print, and which executes exchange and serial communication of signals with a printer engine control portion described hereinafter. Numeral 102 is an engine control portion, which executes control of each unit in a printer engine through the exchange and serial communication of signals with the printer controller.

Numeral 103 denotes a sheet convey control portion which feeds and conveys a sheet to be printed and which

executes sheet conveyance up to discharging of a sheet after printed, based on an instruction from the engine control portion; numeral 104 an optical system control portion which executes control of driving of a scanner motor and ON/OFF of a laser, based on an instruction from the engine control portion; numeral 105 a high voltage control portion which executes output of high voltages necessary for the electrophotographic process including charging, developing, transferring, and so on, based on an instruction from the engine control portion; numeral 106 a fixing temperature control portion which performs control of temperature of a fixing device, based on an instruction from the engine control portion, and which performs detection of abnormality of the fixing device, and the like; numeral 107 a sheet presence/absence sensor input portion which transmits information of sheet presence/absence sensors in a sheet feed portion and in a sheet conveyance path to the engine control portion; numeral 108 a jam detecting portion which detects defective conveyance during sheet conveyance; numeral 109 a breakdown detecting portion which detects a breakdown of functional part in the printer; numeral 110 a toner cartridge detachably attachable to the printer engine.

25 A non-volatile memory 111 capable of transmitting and receiving data to and from the engine control portion is mounted in this toner cartridge, thereby

constituting a configuration enabling reading of data from the engine control portion or writing of data therein.

Conventionally, the engine control portion was
5 configured to count up in the non-volatile memory, data concerning consumption of consumable supplies in the process cartridge, e.g., data about operation of the drum (time of rotation of the drum or the like), the residual amount of toner, etc., and to perform, upon
10 arrival at a predetermined threshold, such control as to inform the printer controller of the fact.

The conventional apparatus was, however, designed without sufficient consideration to timing of carrying out a switch process of primary current values for
15 lengthening the lifetime of the process cartridge and thus had the problem that switching occurred during execution of the electrophotographic process, so as to fail to maintain the uniformity of image quality.

20 SUMMARY OF THE INVENTION

The present invention has been accomplished in view of the above-stated problem and an object of the invention is to provide image processing apparatus that can maintain the uniformity of image quality in
25 printing of identical images and that can drastically improve the performance of the printer.

The other object of the present invention is to

provide an image forming apparatus including an image control portion for expanding predetermined information supplied from an external device, into print information, and a printer control portion for performing print control based on the print information, the image forming apparatus being adapted to print the expanded information in a predetermined recording medium under the print control, the image forming apparatus comprising:

process cartridge means which transmits and receives signals for the print control to and from the printer control portion, which executes an electrophotographic process according to the signals for the print control, and which is detachably attachable to a main body of the image forming apparatus;

non-volatile memory means which stores operation information including information concerning an operation quantity of the process cartridge means and which is mounted in the process cartridge means;

means which performs read/write control of the operation information out of or into the non-volatile memory means, according to the print control from the printer control portion;

switch timing determining means which determines switch timing of a condition for the electrophotographic process, based on the operation

information stored in the non-volatile memory means and a state of the printer control portion; and

switching means which switches the condition for the electrophotographic process at the switch timing.

5 The other objects, configurations, and effects of the present invention will become apparent from the detailed description and drawings which follow.

BRIEF DESCRIPTION OF THE DRAWINGS

10 Fig. 1 is a drawing showing a mechanical configuration of an electrophotographic printer according to the first embodiment of the present invention;

15 Fig. 2 is a block diagram showing the printer control portion according to the first embodiment;

Fig. 3 is a flowchart of a sequence in the engine control portion according to the first embodiment;

20 Fig. 4 is a block diagram showing a system for carrying out switching of primary current according to the first embodiment;

Fig. 5 is a block diagram showing the printer control portion according to the second embodiment;

25 Fig. 6 is a drawing showing job information to be designated for the engine control portion according to the second embodiment of the present invention;

Fig. 7 is a flowchart showing the flow of control of the above engine control portion according to the

second embodiment;

Fig. 8 is a drawing showing an example using an FeRAM or the like as a non-volatile memory according to the third embodiment of the present invention; and

5 Fig. 9 is a block diagram showing the conventional printer control portion.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

First Embodiment

10 Fig. 1 is a drawing showing a mechanical configuration of an electrophotographic printer according to the first embodiment of the present invention.

15 Numeral 1 designates a photosensitive drum for forming an electrostatic latent image, 2 a charging roller for uniformly charging the photosensitive drum 1, 5 an optical unit for scanning the area on the photosensitive drum 1 with a laser beam, 6 the laser beam emitted from the optical unit 5, 3 a developing
20 device for developing with toner, the electrostatic latent image formed on the photosensitive drum 1 with the laser beam, 4 a transferring roller charging device for transferring a toner image on the photosensitive drum 1 onto a predetermined sheet, 7 a fixing device
25 for fusing the toner on the sheet to fix the toner image on the sheet, 8 a standard cassette for carrying sheets for print, 9 a standard cassette sheet feed

roller for picking up a sheet from the standard cassette, 10 discharging rollers for discharging a sheet out of the apparatus, 11 a registration sensor for effecting registration of the leading end for printing of a sheet having been conveyed thereto, 12 a sheet discharge sensor for checking whether a sheet has normally been discharged from the fixing device, and 13 a sensor for detecting presence/absence of a sheet in the standard cassette.

These functional components operate in accordance with instructions from the printer controller described hereinafter. The printer controller performs control to operate the foregoing functional components to implement print processing, based on instructions from an unrepresented image controller.

Numeral 19 represents a non-volatile memory mounted in the cartridge, which stores information, e.g., concerning the photosensitive drum in the cartridge and the volume of toner in the developing device. Data, e.g., about consumption of toner is written from the engine control portion into the memory according to the print operation of the engine or the like. In the engine control portion there exists a memory access means 302 described hereinafter and access is made through the memory access means 302 to the non-volatile memory 19 at predetermined timing, or in accordance with a read request or a write request

from the printer controller.

Fig. 2 is a block diagram showing the printer control portion.

Numeral 201 designates the printer controller, which performs the communication with the host computer, which receives image data and expands the received image data into information for the printer to be able to print, and which executes exchange and serial communication of signals with the printer engine control portion described hereinafter. Numeral 202 denotes the engine control portion, which executes control of each unit in the printer engine through the exchange and serial communication of signals with the printer controller.

Numeral 203 represents the sheet convey control portion which sequentially performs the processes of feeding, conveyance, and discharging of sheet, based on an instruction from the engine control portion; 204 the optical system control portion which performs driving/stopping of the scanner motor, control of emission of laser, etc., based on an instruction from the engine control portion; 205 the high voltage control portion which executes control of respective high voltages of charging, developing, and transferring, based on an instruction from the engine control portion, the high voltage control portion carrying out control to switch process conditions in

accordance with an instruction from a process condition switching means in the engine control portion, which will be described hereinafter. In the present embodiment, the apparatus is adapted to perform control to lower the electric current value with increase in an operation quantity, based on the operation quantity of the drum (total drum rotation time).

Numeral 206 indicates the fixing temperature control portion which carries out control of temperature of the fixing device, based on an instruction from the engine control portion; 207 the sheet presence/absence sensor input portion which detects presence/absence of a sheet in the cassette, presence/absence of a sheet in the conveyance path, etc. to transmit the detection result to the engine control portion; 208 the jam detecting portion which detects an abnormality in conveyance of sheet; 209 the breakdown detecting portion which detects an abnormality of each function in the print process, such as an abnormality of the motor for conveyance of sheet, an abnormality of the fixing device, and so on; 300 the toner cartridge which incorporates the photosensitive drum and the charging and developing functions, which is detachably attachable to the printer engine, which carries the non-volatile memory 301 inside, and which has the function of transmitting and receiving data to and from the engine control portion; 302 the memory

access means in the engine control portion, which performs reading/writing of data from or in the non-volatile memory 301 in the toner cartridge.

5 Signals between the printer controller and the engine control portion will be described.

10 Numeral 210 represents a serial data signal in the serial communication between the print controller and the engine control portion, and this signal handles a command outputted from the printer controller and a signal of status outputted from the engine control portion in two ways. Numeral 211 indicates a synchronous clock in the serial communication, which is outputted from the printer controller to the engine control portion.

15 Numeral 212 stands for /TOP signal which is a vertical synchronizing signal to designate a start of sending of an image signal when a sheet has been conveyed up to the image write position after a start of sheet conveyance; 213 for /BD signal which is a horizontal synchronizing signal for image
20 synchronization in the main scanning direction; 214 for an image signal; 215 for /CCRT signal which is a condition change reporting signal for reporting a condition change from the engine control portion to the
25 printer controller upon occurrence of a condition change, e.g., either of various condition changes in the engine (for example, presence/absence of sheet,

occurrence of jam, and occurrence of breakdown).

The serial communication between the engine control portion and the non-volatile memory will be described below.

5 Numeral 311 represents /CS signal which is a chip select signal outputted from the memory access means to the non-volatile memory; 312 /DOUT signal which is a serial command signal outputted from the memory access means to the non-volatile memory; 313 /DIN signal which is a data signal returned from the non-volatile memory to the memory access means; 314 /CLK signal which is a serial synchronous clock outputted from the memory access means to the non-volatile memory.

10 Numeral 303 denotes a switch timing control means in the engine control portion, which monitors the state of the engine control portion and which determines switch timing of the process conditions; 304 a process condition switching means which gives the high voltage control portion an instruction to change the predetermined high voltage outputs to outputs matching with the memory contents, in accordance with an instruction from the switch timing control means 303.

15 In the present embodiment, the switch timing control means judges whether the engine control portion is in the print operation, i.e., whether it is in control of sheet conveyance or in output for charging or developing of the electrophotographic process for

printing, and determines the switch timing at the time when the both are negative; not in the sheet conveyance and not in the electrophotographic process.

With determination of the switch timing, the process condition switching means is informed of a primary charging current value based on the drum operation quantity data in the memory, and the new set value will be outputted upon next application of high voltage.

Fig. 3 is the flowchart showing the above sequence of the engine control portion.

First, the engine control portion checks whether a print request from the controller is present (step S301).

When the condition for switching of primary current is met, data of the sum of drum driving time is read from the non-volatile memory in the cartridge, which stores the data corresponding to the sum of past drum driving time (step S302).

It is then determined whether the sum exceeds T_d being a threshold of primary current (step S303). When the sum exceeds T_d , the primary current is set to I_1 (step S304). When it does not exceed T_d , the primary current is set to I_2 (step S305).

After that, the engine control portion starts driving the motor for printing, starts the optical system including the scanner motor and others, starts

the various high voltages, and starts the temperature control of the fixing device (step S306).

5 The engine control portion starts measuring of the drum driving time at the same time as the start of driving of the motor (step S307).

10 It is then determined whether the print is finished (step S308). When it is determined that the print is finished, the engine control portion terminates the fixing temperature control, stops the motor, breaks the high voltages, stops the optical system, and terminates the driving of the drum finally (step S309).

15 Then the engine control portion stops the measuring of the driving time of the drum (step S310) and it adds the result of the measuring of drum driving time at that time to the sum of drum driving time in the non-volatile memory in the cartridge and again stores the result of the addition in the non-volatile memory (step S311). After that, the engine control
20 portion goes into the first state of waiting for a print request (step S301).

According to the sequence as described above, the switching of primary current is not effected instantly, but is postponed at least to the end of print.

25 Fig. 4 is a block diagram showing a system for carrying out the switching of primary current.

Numerical 401 designates a CPU presiding over the

center of the engine control portion, only a high voltage control part of which is extracted in the illustration herein. Numeral 402 denotes a high voltage control circuit, which controls output of the
5 respective high voltages for primary charging, developing bias, and transferring charging and which performs the switching of output in accordance with an instruction from the CPU. Numeral 403 represents a primary charging voltage setting circuit which outputs
10 the primary charting voltage in a value designated from the CPU, to the charging roller 2; 404 a developing bias setting circuit which outputs a developing bias in accordance with an instruction from the CPU; 405 a
15 transferring voltage setting circuit which outputs the transferring voltage in accordance with an instruction from the CPU.

The CPU can turn the primary charging on or off by PreON signal. The CPU can also switch the primary
20 charging current value between I1 and I2 by High signal.

Second Embodiment

The second embodiment will be described next. Since the mechanical configuration of the electrophotographic printer in the second embodiment is
25 similar to that in Fig. 1 in the first embodiment, the description thereof is omitted herein.

Fig. 5 is a block diagram showing the printer

control portion according to the second embodiment.

Numeral 201 designates the printer controller, which performs the communication with the host computer, which receives image data and expands the received image data into information for the printer to be able to print, and which executes the exchange and serial communication of signals with the printer engine control portion described hereinafter. Numeral 202 denotes the engine control portion, which executes the control of each unit in the printer engine through the exchange and serial communication of signals with the printer controller.

Numeral 203 represents the sheet convey control portion which sequentially performs the processes of feeding, conveyance, and discharging of sheet, based on an instruction from the engine control portion; 204 the optical system control portion which performs driving/stopping of the scanner motor, control of emission of laser, etc., based on an instruction from the engine control portion; 205 the high voltage control portion which executes control of the respective high voltages of charging, developing, and transferring, based on an instruction from the engine control portion, the high voltage control portion carrying out control to switch the process conditions in accordance with an instruction from the process condition switching means in the engine control

portion, which will be described hereinafter. In the present embodiment, the apparatus is adapted to perform the control to lower the electric current value with increase in an operation quantity, based on the operation quantity of the drum (total drum rotation time).

Numeral 206 indicates the fixing temperature control portion which carries out the control of temperature of the fixing device, based on an instruction from the engine control portion; 207 the sheet presence/absence sensor input portion which detects presence/absence of a sheet in the cassette, presence/absence of a sheet in the conveyance path, etc. to transmit the detection result to the engine control portion; 208 the jam detecting portion which detects an abnormality in conveyance of sheet; 209 the breakdown detecting portion which detects an abnormality of each function in the print process, such as an abnormality of the motor for conveyance of sheet, an abnormality of the fixing device, and so on; 300 the toner cartridge which incorporates the photosensitive drum and the charging and developing functions, which is detachably attachable to the printer engine, which carries the non-volatile memory 301 inside, and which has the function of transmitting and receiving data to and from the engine control portion; 302 the memory access means in the engine control portion, which

performs reading/writing of data from or in the non-volatile memory 301 in the toner cartridge.

Signals between the printer controller and the engine control portion will be described.

5 Numeral 210 represents a serial data signal in the serial communication between the print controller and the engine control portion, and this signal handles a command outputted from the printer controller and a signal of status outputted from the engine control
10 portion in two ways. Numeral 211 indicates a synchronous clock in the serial communication, which is outputted from the printer controller to the engine control portion. Numeral 212 stands for /TOP signal which is a vertical synchronizing signal to designate a
15 start of sending of an image signal when a sheet has been conveyed up to the image write position after a start of sheet conveyance; 213 for /BD signal which is a horizontal synchronizing signal for image
20 synchronization in the main scanning direction; 214 for an image signal; 215 for /CCRT signal which is a condition change reporting signal for reporting a condition change from the engine control portion to the printer controller upon occurrence of a condition
25 change, e.g., either of various condition changes in the engine (for example, presence/absence of sheet, occurrence of jam, and occurrence of breakdown). The serial communication between the engine control portion

and the non-volatile memory will be described below.

Numeral 311 represents /CS signal which is a chip
select signal outputted from the memory access means to
the non-volatile memory; 312 /DOUT signal which is a
5 serial command signal outputted from the memory access
means to the non-volatile memory; 313 /DIN signal which
is a data signal returned from the non-volatile memory
to the memory access means; 314 /CLK signal which is a
serial synchronous clock outputted from the memory
10 access means to the non-volatile memory.

In the first embodiment, the switch timing of
primary current was determined based on the information
intrinsic to the engine, i.e., based on whether a
transition is made into the standby state. In the
15 second embodiment, however, the engine control portion
determines the switch timing of primary current value,
based on reception of job information from the printer
controller, i.e., information about a predetermined
heap of print works from the user under print requests
20 from the host computer to the printer controller.

The job information from the printer controller is
transmitted through the serial communication between
the foregoing printer controller and the engine control
portion.

25 Numeral 303 denotes the switch timing control
means in the engine control portion, which monitors the
state of the engine control portion and which

determines the switch timing of the process conditions;
304 the process condition switching means which gives
the high voltage control portion an instruction to
change the predetermined high voltage outputs to
5 outputs matching with the memory contents, in
accordance with an instruction from the switch timing
control means 303.

In the present embodiment, the switch timing
control means performs the switch work at the time when
10 the engine has completed the print of a series of print
jobs designated from the printer controller, based on
the job information designated from the printer
controller, to go into the standby state, and the
control means then executes the print at the primary
15 current value thus switched, from a next designated
print job.

Fig. 6 shows the job information designated for
the engine control portion by the print controller in
the serial communication. The serial communication is
20 of a 16-bit configuration and the highest four bits
thereof indicate a job information designating command.
Eleven bits below them except for the parity bit
designate the number of prints in a job printed next.
In the present embodiment, the figure shows such an
25 illustration that the job information designating
command is indicated when the highest four bits are
0001 B.

This command demonstrates its effect when it is outputted prior to output of a print request from the printer controller. Namely, by issuing the foregoing job designating command prior to the print request, it
5 is recognized how many prints from the next requested print are in one job.

Fig. 7 is a flowchart showing the control of the above engine control portion.

First, the engine control portion determines
10 whether all printing of a print job in the number designated from the printer controller is finished (step S701). When all is finished, the engine control portion starts checking whether a next job is designated (step S702). When there is a designated
15 print job from the printer controller, the number of print is stored (step S703). When there is no designation, the engine control portion sets job designation of one print as a default value (step S704).

20 After that, the engine control portion checks whether a print request is present (step S705). When there is a print request, the engine control portion reads the drum driving time used as a threshold for switching of primary current from the data stored in
25 the non-volatile memory in the cartridge (step S706). When there is no print request, the engine control portion returns to step S701. After the process at

step S706, the engine control portion determines whether the drum driving time exceeds the predetermined time (step S707). When it is determined as a result that the drum driving time does not exceed T_d being the predetermined threshold, the engine control portion sets the initial primary current value I_1 (step S708). When the drum driving time exceeds the threshold T_d , it is determined whether the printer is at the first page of the job (step S709). When it is at the first page, the primary current value is set to I_2 (step S710).

After that, the engine control portion starts driving the motor for the print, starts the optical system including the scanner motor and others, starts the various high voltages, and starts the temperature control of the fixing device (step S711). Then the engine control portion executes the actual print operation and the measurement to count the drum driving time (step S712). It is then determined whether the print of one page is finished (step S713). When it is determined that the print is finished, the print number is counted up (step S714); the break processes of the high voltages, the optical system, etc. are carried out (step S715); the measuring of the drum driving time is terminated (step S716); the result of the measuring of the drum driving time at that time is further added to the sum of drum driving time in the non-volatile memory in the cartridge and the result of the addition is

again stored in the non-volatile memory (step S717).

After completion of the above, the engine control unit returns to the first process (step S701).

According to the above processing, before
5 completion of printing in the print number of the job
designated from the printer controller, the engine
control portion does not switch the primary current in
the middle of the job before finishing the printing
operation through the print number of the designated
10 job even if the sum of drum driving time exceeds the
predetermined threshold to meet the primary current
switch condition. In addition, switching is not
effected during the print operation, either, whereby
the primary current can be switched at optimal timing.

15 Third Embodiment

In the first and second embodiments, the serial
communication is implemented by signals through wires
between the non-volatile memory and the engine control
portion.

20 However, it is also feasible to employ such a
configuration that the non-volatile memory such as an
FeRAM or the like is mounted in the cartridge and the
exchange of data is implemented with the memory by use
of electromagnetic coupling through coils, as shown in
25 Fig. 8, and this configuration according to the present
invention can also achieve the same effects as in the
case of the wire communication.

Other Embodiments

The present invention may be applied to systems comprised of a plurality of devices (e.g., a host computer, an interface device, a reader, a printer, etc.) and also to an apparatus consisting of one device (e.g., a copier, a facsimile device, etc.).

It is also needless to mention that the object of the present invention can also be accomplished by supplying a storage medium (or recording medium) storing the program code of software for realizing the functions of the aforementioned embodiments, to a system or apparatus and making a computer (or CPU or MPU) of the system or apparatus read and execute the program code stored in the storage medium. In this case, the program code itself read out of the storage medium realizes the functions of the foregoing embodiments, so that the storage medium storing the program code constitutes the present invention.

It is also needless to mention that, in addition to the configuration wherein the computer executes the program code thus read to implement the functions of the foregoing embodiments, the invention also embraces such a configuration that, based on instructions of the program code, an operating system (OS) operating on the computer executes part or the whole of the actual processing and the processing implements the functions of the foregoing embodiments.

Further, it is also a matter of course that the present invention also embraces such a configuration that the program code read out of the storage medium is written into a memory in a function extension card
5 inserted into a computer or in a function extension unit connected to a computer, then a CPU in the function extension card or in the function extension unit executes part or the whole of the actual processing, based on the instructions of the program
10 code, and the processing implements the functions of the foregoing embodiments.

When the present invention is applied to the above storage medium, the program code corresponding to the flowcharts described previously (as shown in Fig. 3
15 and/or Fig. 7) is stored in the storage medium.

According to the present invention, as described above, the switch instruction to switch the electrophotographic process condition is given when the engine control portion is not in execution of the
20 electrophotographic process, whereby switching of the process condition is not effected for the switching process of the primary current value for extending the lifetime of the drum, which makes it feasible to achieve the effects of maintaining the uniformity of
25 image quality in printing of identical images and drastically improving the performance of the printer.

The present invention was described above with

some preferred embodiments thereof, but it is noted
that the present invention is by no means intended to
be limited to these embodiments and it is apparent that
the present invention can involve various modifications
5 and applications in the scope of claims.

10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
2228
22